


# YOUR EV5 APARTMENT STATION USER GUIDE

**1**




The visitor presses the button for your flat number or dials your number on the main entrance panel

**2**




Your apartment station will ring. If the call is not answered the system will reset to allow other calls.

**3**



Pick up your handset if you wish to speak.


**4**



Call tone volume    Timed privacy    Call back    Door release


1. To answer the call remove the handset from the cradle and speak to the visitor. (You have approx. 2 minutes to speak to the visitor and then the system will reset).
2. To let the visitor gain access, press the lock release button and this will open the door for approximately 10 seconds.
3. When you have completed the call, replace the handset to reset the system.

**5**




If you press the "lock release" button the main entrance panel will beep. Your visitor can now enter.

**6**




Please ask your visitor to ensure the door closes behind them. Replace your handset now.

**7**




If you do not want to be disturbed press the "privacy" button once. The red light will come on. Please note: you will not receive any calls for 12 hours when the red light is on. If you wish to receive calls before the 12 hour time-out press the "privacy" button again and the red light will go off.

**8**



Remember: it is up to you to control who comes into the building. Only let people in if you are sure of their identity. If you do not wish to speak or let them in simply replace the handset.

**9**



For your entry into the building place your token to the reader and open the door.

**10**



For your exit from the building push the exit button and open the door.